

620-011
Strain Relief
Rotatable Coupling - Straight and 90°






62

**CONNECTOR
DESIGNATOR**

H

**ROTATABLE
COUPLING**



**See inside back
cover fold-out or
pages 13 and 14 for
Tables I and II.**

1. Cable Entry is defined as the accommodation entry for the wire bundle or cable. Dimensions are not intended for inspection criteria.
2. Metric dimensions (mm) are indicated in parentheses.





TABLE III: CABLE ENTRY

Shell Size	E Max	F Max	G Max	H Max	Cable Entry	
					Closed	Open
09	.830 (21.1)	.850 (21.6)	.704 (17.9)	.808 (20.5)	.098 (2.5)	.234 (5.9)
11	.850 (21.6)	.900 (22.9)	.786 (20.0)	.867 (22.0)	.153 (3.9)	.234 (5.9)
13	.900 (22.9)	1.100 (27.9)	.979 (24.9)	.929 (23.6)	.190 (4.8)	.328 (8.3)
15	.900 (22.9)	1.150 (29.2)	1.039 (26.4)	.992 (25.2)	.260 (6.6)	.457 (11.6)
17	.940 (23.9)	1.300 (33.0)	1.188 (30.2)	1.056 (26.8)	.283 (7.2)	.614 (15.6)
19	1.020 (25.9)	1.500 (38.1)	1.300 (33.0)	1.233 (31.3)	.325 (8.3)	.634 (16.1)
21	1.070 (27.2)	1.600 (40.6)	1.425 (36.2)	1.296 (32.9)	.343 (8.7)	.698 (17.7)
23	1.190 (30.2)	1.700 (43.2)	1.550 (39.4)	1.358 (34.5)	.381 (9.7)	.823 (20.9)
25	1.220 (31.0)	1.800 (45.7)	1.675 (42.5)	1.420 (36.1)	.418 (10.6)	.853 (21.7)

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Glenair:

[620HA011M09-439](#) [620HA011M11-439](#) [620HA011M13-439](#) [620HA011M15-439](#) [620HA011M17-439](#)
[620HA011M25-439](#) [620HS011F13](#) [620HS011M09-439](#) [620HS011M11-439](#) [620HS011M13-439](#) [620HS011M13-701](#)
[620HS011M15-439](#) [620HS011M15-7L](#) [620HS011M17-439](#) [620HS011M19-401](#) [620HS011M19-701](#) [620HS011M23-](#)
[439](#) [620HS011M25-401](#) [620HS011M25-701](#) [620HS011NF15-715](#) [620HS011M19-439](#) [620HS011M21-439](#)
[620HS011M25-439](#) [620HS011W11](#) [620HA011M23-439](#) [620HA011M21-439](#) [620HS011MR13](#)